



2010S2 Integrated Amplifier

- Power Output (Stereo) : 75 Watts per channel at 1KHz into 8 Ohms
- Input Sensitivity : 250mV
- Input Impedance : >14K Ohms, line input
- Pre-amplifier Output : gain + 18dB
- Frequency Response : 20Hz - 20KHz \pm 0.5dB
- Total Harmonic Distortion : <0.05% at 1KHz, rated power
- Signal to Noise : >100dB, A weighted, ref rated output
- Channel Separation : 20Hz - 20KHz, >60dB
- Mains Supply : 110/120V or 220/240V, 50/60Hz (factory set)
- Power Consumption : <200VA (both channels driven, 8 Ohms load)
- Dimensions - H x W x D : 90mm x 440mm x 310mm
- Nett Weight (unpacked) : 7kg
- Gross Weight (packed) : 9kg



2010S2 CD Player

- Output Level : 2V RMS
- Frequency Response : 20Hz - 20KHz \pm 0.03dB
- Total Harmonic Distortion : <0.008%, 20Hz - 20KHz, 0dBFs
- Signal to Noise Ratio : >100dB, A weighted
- Digital Outputs : SP/DIF, Coaxial and "Toslink" Optical
- Mains Supply : 110/120V or 220/240V, 50/60Hz (factory set)
- Power Consumption : <25VA
- Dimensions - H x W x D : 90mm x 440mm x 300mm
- Nett Weight (unpacked) : 5kg
- Gross Weight (packed) : 7kg



2010S2 Power Amplifier

- Power Output (Stereo) : 75 Watts per channel at 1KHz into 8 Ohms
- Input Sensitivity : 1V, gain + 24dB
- Input Impedance : >18K Ohms
- Frequency Response : 20Hz - 20KHz \pm 0.5dB
- Total Harmonic Distortion : <0.02% at 1KHz, rated power
- Signal to Noise : >110dB, A weighted, ref rated output
- Channel Separation : >80dB, 20Hz - 20KHz
- Mains Supply : 110/120V or 220/240V, 50/60Hz (factory set)
- Power Consumption : <250VA, both channels driven, 8 Ohms load
- Dimensions - H x W x D : 90mm x 440mm x 310mm
- Nett Weight (unpacked) : 7kg
- Gross Weight (packed) : 9kg





2010S2 Integrated Amplifier

1. High capacity, 200VA custom-made toroidal power transformer and power supply capacitors
2. Improved all-aluminium casework and extruded front panel to control resonance and stray electro-magnetic fields
3. High quality capacitors used in the signal path
4. Uniquely tuned short signal and power supply path PCB
5. Cascode circuitry utilised for improved power supply immunity
6. Sanken bipolar output transistors for dynamics and performance
7. Separate pre-amp output
8. Bi-wiring compatible
9. 75 watts per channel into 8 Ohms
10. Full-function remote control
11. Three-year guarantee



2010S2 Compact Disc Player

1. Single PCM 1716 24 bit DAC fitted to provide very high resolution
2. CD display can be turned off for improved sound quality
3. Highly optimised audio output circuitry with multiple stages of supply regulation
4. Large toroidal power transformer with separate windings for CD transport mechanism and audio stages
5. Employment of a high-stability crystal clock reference and dedicated, power supply regulator for the transport and audio stages to ensure low jitter performance
6. High quality double-sided PCBs for optimum layout and screening
7. All-aluminium casework and extruded front panel to control resonance and stray electro-magnetic fields
8. Full-function remote control
9. Three-year guarantee



2010S2 Power Amplifier

1. High capacity 200VA custom-made toroidal power transformer and supply capacitors
2. All-aluminium casework and extruded front panel to control resonance and stray electro-magnetic fields
3. High quality capacitors used in the signal path
4. Very clean and extended low frequency performance
5. Bi-Wiring compatible
6. 75 watts per channel into 8 Ohms
7. Three-year guarantee

Also available in **BLACK**